

DESCRIPTION:

The CTH-100 is the Clamp-On (also called Split-Core) current transducer for measurement of DC, AC and pulsed currents, with the galvanic isolation between the primary circuit and the secondary circuit. The CTH product series provides current transducers for the nominal measured currents in the range of 100A to 10kA. The CTH-100 is configured for the nominal measured (primary) current of 100A.

CTH-100 current transducers consist of two parts: transducer head and transducer electronics, connected with the multi-paired shielded cable of up to 10m length.

The transducer head encloses two magnetic split-cores, with the two high resolution Hall sensors for the differential magnetic measurement around the current carrying conductor.

For the elimination of the remanent magnetic field in the split-cores, the CTH-100 utilizes an advanced degaussing (demagnetization) process. A pushbutton is available at the front panel of the transducer for the initialization of the degaussing process. A dedicated LED indicates that the transducer output is not valid (LED is red) during the demagnetization process.



Figure 1: CTH-100 Configuration

FEATURES:

- Measurement of DC, AC and pulsed currents, $I_{PN} = 100 \text{ A} (I_{PN} \text{nominal primary current})$
- Frequency bandwidth from DC to 3kHz (total accuracy < 0.1%)
- Clamp-On (Split-Core) for easy installation; the installation does not require an interruption of the primary current circuit
- Closed loop current transducer using the high resolution Hall sensors
- Superior total accuracy <0.1%
- Excellent linearity
- Very small offset
- Very low temperature offset drift in the temperature range of $-40^{\circ}C \div +70^{\circ}C$
- Very high immunity to the external interference
- Clean recovery from very high transient overload
- Differential output at BNC connector
- Head aperture diameter (max. conductor diameter) 20mm

North American Distributor: GMW Associates	Rev. 2.6
955 Industrial Road, San Carlos, CA 94070, USA	July 2018
Web: <u>www.gmw.com</u> ; E-mail: <u>sales@gmw.com</u>	Dama 1/6
Phone: +1 (650) 802 8292; Fax: +1 (650) 802 8298	Page 1/0
	North American Distributor: GMW Associates 955 Industrial Road, San Carlos, CA 94070, USA Web: <u>www.gmw.com</u> ; E-mail: <u>sales@gmw.com</u> Phone: +1 (650) 802 8292; Fax: +1 (650) 802 8298



TYPICAL APPLICATIONS:

- Power Electronics
- Motor & Generator Control
- Electromechanical Systems
- Battery Charging
- Transit & Off Road Vehicles
- Process Control

ABSOLUTE MAXIMUM RATINGS ^{(1) (2)}:

In accordance with the absolute maximum rating system (IEC60134).

Symbol	Parameter	Min.	Тур.	Max.	Units	Remarks
T _{stg}	Storage Temperature	-40		+100	°C	
T _{amb}	Ambient Temperature	-40		+70	°C	
T _B	Busbar temperature	-40		+100	°C	

⁽¹⁾ Absolute Maximum Ratings" indicate the limits beyond which a damage to the device may occur. Operating Ratings indicate the conditions for which the device is functional, but does not ensure the performance limits specified.

⁽²⁾ The output is short-circuit protected.

WARNING: Stresses beyond those listed under "Absolute maximum ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of this specification are not implied. Exposure to absolute maximum rating conditions for extended periods may affect the device reliability.

RECOMMENDED OPERATING CONDITIONS:

Symbol	Parameter	Min.	Тур.	Max.	Units	Remarks
T _{amb}	Ambient Temperature	-40	+25	+70	°C	
V_{ac}	Supply Voltage	90		264	V_{ac}	

SENIS AG	North American Distributor: GMW Associates	Rev. 2.6	
Neuhofstrasse 5a, 6340 Baar, Switzerland	955 Industrial Road, San Carlos, CA 94070, USA	July 2018	
Web: www.senis.ch ; E-mail: current.sensors@senis.ch	Web: <u>www.gmw.com</u> ; E-mail: <u>sales@gmw.com</u>	Page 2/6	
Phone: +41 (44) 508 7029; Fax: +41 (43) 205 2638	Phone: +1 (650) 802 8292; Fax: +1 (650) 802 8298		

ELECTRICAL CHARACTERISTICS:

At $T_A = 25^{\circ}C$, $R_M = 5\Omega$ (built in resistor)

	Symbol	Min.	Тур.	Max.	Units	Conditions
Supply Voltage	V _{SUP}		230		V _{AC}	
Primary nominal current rms	I _{PN}			100	А	
Max. primary current / measurement range	I _{PM}			150	А	
Secondary winding resistance	Rs			13.5	Ω	Each secondary winding
Number of secondary turns	Ns		1000			Each winding
Sensitivity (differential output)	S		10		mV/A	
Electrical offset current	I _{OE}		±0.05		А	T=25°C
Magnetic offset current due to the core hysteresis	I _{OM}		±0.02		A	-After 3 x $I_{\rm PN}$ -The polarity depends on the polarity of $I_{\rm PN}$
Conductor position	Centre	-		_		
Sensitivity error	ε _G	-0.10		0.10	% of N_{S}	T=25°C
Linearity error	ε _L	-0.03		0.03	% of $I_{\mbox{\scriptsize PN}}$	T=25°C
Overall accuracy at I _{PN}	X _C	-0.08		0.08	% of $I_{\mbox{\scriptsize PN}}$	T=25°C Note 1
Frequency bandwidth	BW		3		kHz	Xc < 0.1%of I _{PN}
Conductor position	Out of cer	ntre, max.	to the core	es	1	
Sensitivity error	ε _G	-0.70		0.70	%	T=25°C
Linearity error	ε _L	-0.40		0.40	% of $I_{\mbox{\scriptsize PN}}$	T=25°C
Overall accuracy at I _{PN}	X _C	-0.15		0.15	$\%$ of I_{PN}	T=25°C Note 1
Conductor position	Skewed, max. to the cores (40°)					
Sensitivity error	ε _G	-0.85		0.85	%	T=25°C
Linearity error	ε _L	-0.85		0.85	% of $I_{\mbox{\scriptsize PN}}$	T=25°C
Overall accuracy at I _{PN}	X _C	-0.20		0.20	$\%$ of I_{PN}	T=25°C Note 1
External field immunity		-			1	1
Sensitivity to the external	S _E		0.1		% of S	Note 2,3
magnetic field	S _E		0.1		% of S	Note 2,4

Note:

1 - calculated based on equation (2)

2 - DC current through the external conductor: 100A

3 - See figure 2, a distance between the CTH-100 head and an external conductor is 90mm

4 - See figure 3, no distance between the CTH-100 head and an external conductor

$$Xc = \sqrt{I_{OE}^{2} + (\epsilon_{G} \cdot \frac{I_{PN}}{N_{S}})^{2} + (\epsilon_{L} \cdot \frac{I_{PM}}{N_{S}})^{2} + I_{OM}^{2}}$$
(1)
$$Xc (\% \text{ of } I_{PN}) = 100 \cdot \frac{\sqrt{I_{OE}^{2} + (\epsilon_{G} \cdot \frac{I_{PN}}{N_{S}})^{2} + (\epsilon_{L} \cdot \frac{I_{PM}}{N_{S}})^{2} + I_{OM}^{2}}}{I_{PN}}$$
(2)

ev. 2.0	
ıly 2018	
Daga 2/6	
rage 3/6	
;	





Figure 2: Position of an external conductor (carrying the current of 100A) near the CTH-100 head



Figure 3: Position of an external conductor (carrying the current of 100A) along the CTH-100 head

SENIS AG	North American Distributor: GMW Associates	Rev. 2.6
Neuhofstrasse 5a, 6340 Baar, Switzerland	955 Industrial Road, San Carlos, CA 94070, USA	July 2018
Web: <u>www.senis.ch</u> ; E-mail: <u>current.sensors@senis.ch</u>	Web: <u>www.gmw.com</u> ; E-mail: <u>sales@gmw.com</u>	Demo 4/6
Phone: +41 (44) 508 7029; Fax: +41 (43) 205 2638	Phone: +1 (650) 802 8292; Fax: +1 (650) 802 8298	Page 4/6



DIMENSIONS:







(dimensions in mm)





Figure 4: Dimensions of the CTH-100 current sensing head

SENIS AG	North American Distributor: GMW Associates	Rev. 2.6	
Neuhofstrasse 5a, 6340 Baar, Switzerland	955 Industrial Road, San Carlos, CA 94070, USA	July 2018	
Web: <u>www.senis.ch</u> ; E-mail: <u>current.sensors@senis.ch</u>	Web: <u>www.gmw.com</u> ; E-mail: <u>sales@gmw.com</u>	Dere F/6	
Phone: +41 (44) 508 7029; Fax: +41 (43) 205 2638	Phone: +1 (650) 802 8292; Fax: +1 (650) 802 8298	Page 5/6	





Figure 5: Dimensions of the CTH-100 electronic box

PACKAGING INFORMATION:

Packaging contains:

- CTH-100 transducer head
- CTH-100 transducer electronic box
- Cross connection cable between the head and the electronic box. The standard cable length is 2m (up to 10m can be provided on request)
- Power supply

The product is compliant with EU RoHS directives.

SENIS AG	North American Distributor: GMW Associates	Rev. 2.6
Neuhofstrasse 5a, 6340 Baar, Switzerland	955 Industrial Road, San Carlos, CA 94070, USA	July 2018
Web: <u>www.senis.ch</u> ; E-mail: <u>current.sensors@senis.ch</u>	Web: <u>www.gmw.com</u> ; E-mail: <u>sales@gmw.com</u>	Demo 6/6
Phone: +41 (44) 508 7029; Fax: +41 (43) 205 2638	Phone: +1 (650) 802 8292; Fax: +1 (650) 802 8298	Page 6/6